



Casambi DMX Controller

AL-CTRL-CAS-DMX

1 Universe



DESCRIPTION

This Casambi-enabled DMX controller makes it easy to wirelessly connect DMX-512 lighting fixtures to a Casambi network. Designed for full-color and tunable white applications, this product offers up to 12 controllable DMX channels configured and controlled directly through the Casambi app, providing intuitive, app-based control over multi-channel LED lighting systems.

Powered by a 12VDC or 24VDC Class 2 power supply, the controller transmits a single DMX universe via Bluetooth and features a built-in long-range mesh radio module. With selectable Casambi profiles, users can easily configure the controller for 4, 8, or 12 channel operation, making it a flexible choice for everything from simple to complex lighting control.

KEY FEATURES



DMX



Space Saving



Wireless



Mesh Network

PRODUCT SPECIFICATION CHART

PHYSICAL		CONTROL	
Height	2.20" Tall (56mm)	Dimmable	Yes (via Casambi app)
Width	1.20" Wide (30mm)	Dimming Compatibility	Pulse Width Modulation (PWM)
Depth	0.70" Deep (18mm)	DMX Compatibility	DMX-512 (single universe)
Weight	0.81 oz (23g)	DMX Channels	12
Warranty	1 Year	ENVIRONMENTAL	
ELECTRICAL		IP Rating	IP20
Input & Output Voltage	12-24VDC	Suitable Uses	Dry Locations Only (Indoor Only)
Max Input & Output Current	30mA	Max Operating Temp	-25°C to 45°C (-13°F to 113°F)
Wire Connections	14-22 AWG Solid or Stranded	STANDARDS & CERTIFICATIONS	
DO NOT USE WITH MLV POWER SUPPLIES		ETL Listed CSA CE	

